

7RRLsssssXXXXsIAACs[DC4]

Where,	7	: Protocol number
	RR	: Receiver number
	L	: Line number
	sssss	: Spaces
	XXXX	: Account code
	s	: Space
	I	: Event code from the SESCOA 3000 event code table
	AA	: Two digit zone codes or first two digit user codes
	C	: Space if zone report, or last digit user code
	s	: Space.
	[DC4]	: Terminator

The following gives the detailed information:

## *Sescoa Library*

Event to be reported	Report	IAACs
A	Alarm 00-99	A99ss
D	Trouble 00-99	T99ss
E	Restore 00-99	R99ss
OP	Open, no user	Ossss
IOP	Open with ID	O123s
FOP	Fail to OP	Ussss
EOP	OP out of window	#ssss
LOP	OP out of window	#123s
CL	Close, no ID	Cssss
ICL	Close with ID	C123s
FCL	Fail to CL	Qssss
ECL	CL out of window	\$ssss
LCL	CL out of window	\$123s
DU	Duress	Yssss
24H	24 Hour Report	Hssss
CH	Test	Kssss
AC	AC fail	Jssss
EAC	AC Restore	Mssss
ELO	Power Restore	Essss
LO	Low battery	Fssss
FLO	No battery	Gssss
dBL	Bell trouble	Zssss
EBL	Bell restore	!ssss
dPL	Phone trouble	Vssss
EPL	Phone restore	Xssss