

**Available on the 1.81SV**

**Handshakes**

1400Hz, 2300Hz and FSK Handshakes are accepted, the handshake sent by the Varitech receiver is 2300Hz.

**Kiss off**

The kiss off used for Varitech is fifteen (15) burst at the end of the transmission. The burst are sent approxemently 258ms after the data transmission. Each burst is 55ms in lenght at 2300Hz. The time between each burst is 55ms.

After the kiss off, the panel may hang up or send additional alarm signals if any.

**Varitech Library**

The Varitech format 4/1, 4/2 library.

Message	Code	Event Code
Alarm	0X	A
Fire	1X	A
Panic	2X	A
Burgl	3X	A
Medic	4X	A
Auxil	5X	A
Bypass	6X	A
Inactive	7X	A
Alarm	8X	A
Alarm	9X	A
Alarm	AX	A
Open	BX	O
Close	CX	C
Abort/Test	DX	\
Restr	EX	R
Trble	FX	T